

## DIGITAL RCD TESTER

**MODEL TES-1900A (230V)**  
**TES-1900B (110V)**

- Custom microprocessor controlled for highest accuracy and reliability.
- 3 LED 's for checking correct wiring status.
- 0 and 180 degree phase angle switch permits quick tests and consistent readings.
- Digital read out of tripping time.
- Large custom digital display readout on all models.
- Visual indication of reversed phase and neutral wiring at socket.
- Resilient case made from modern plastics to take everyday knock and brings.



**TES-1900**

### Specification

<b>Rated Tripping Current</b>	10 / 20 / 30 / 100 / 300 / 500mA
<b>Fault Condition Setting</b>	x1/2 , x1 , x5
<b>Fault Trip Time</b>	2000ms , 40ms (x5)
<b>Low Set Resolution</b>	1ms ( x1/2 , x1 ) , 0.1ms ( x5 )
<b>Trip Time Accuracy</b>	+/- (1% rdg + 2dgts)
<b>Operating Voltage</b>	230V +/- 10% , 50/60Hz
<b>Withstand Voltage</b>	3000V AC for 1 minute
<b>Dimensions</b>	200(L) x 140(W) x 95(H)mm
<b>Weight</b>	About 800g
<b>Operating Temperature and Humidity</b>	0°C to 40°C (32°F to 104°F), Below 80% RH
<b>Storage Temperature</b>	-10°C to 60°C (14°F to 140°F)
<b>Accessories</b>	Test Lead with IEC Connector.